

LIGHT CONTROL BOX

The AC power of 600W at maximum fed into the control box is divided into 2 lines each of which can support up to 300W of load (around 10 LED lights) . The control for lights on the same line is by nature synchronized meanwhile synchronization of control over both lines (all lights) is possible.

Features

1. Maximum load of 600W with power indicator.
2. Made from fire-proof ABS material.
3. Electrical overload & leakage protection.
4. Two control modes-manual mode and timer mode in which the ON/OFF time of load can be set.
5. IP44 rating suitable for outdoor use.
6. A remote control is provided to interact with control box from distance.
7. Simple and easy operation with 4 keys.
8. 10 effects are all sequenced numbered; RESET key set all lights to the first effect.
9. "POOL and SPA" key are used to change effect of lights connected to Pool line and Spa line respectively.



Underwater Light Control Box

IP44 CE RoHS COMPLIANT 2011/65/EU SAA



Remote Control

Code	Model No	Description
08040009	N/A	Underwater Light Control Box with Remote Controller (2*300W/220-240V)
08040020	N/A	Underwater Light Control Box with Remote Controller (2*300W/110V/60Hz)

